

## KOMPONENTNYCKEL COMPONENT KEY

### HUR MAN FINNER KOMPONENTENS FULLSTÄNDIGA DATA

1. Sök upp det kretsschema i vilket komponenten finns och anteckna komponentens beteckning och värde.
2. Gå in i den komponentlista (specifikation) som hör till kretsschemat, sök upp komponentens beteckning och läs av artikelnumret (SRA-numret).
3. Slå upp komponentens huvudrubrik i komponentnyckeln, sök upp artikelnumret och läs av komponentens övriga data.

### HOW TO FIND COMPLETE DATA OF COMPONENTS

1. Locate the circuit diagram comprising the component and make a note of designation and value.
2. Refer to the component list (specification) relevant to the diagram and locate the component. Make a note of the SRA article number.
3. Find the relevant heading in the Component Key, locate the SRA reference number and make a note of the additional data of the component.

KONDENSATORER  
CAPACITORS

## C - 500 Automatic

SRA-nr SRA-no	Exempel på fabrikat Example of manufacturer	Typ Type	Arbets- spänning Working voltage ( V )	Kapacitanstolerans Capacitance tolerance	Anmärkning Note
<b>Keramiska Ceramic</b>					
NA 104480	Ferroperm	9/0116,3 insul	250=	± 2%	TK=-150x10 <sup>-6</sup> /°C
NA 104882	Philips	2222 700..... typ 1	350=	C≤4,7pF±0,5pF 6,8pF≤C≤10pF±1pF C≥15pF±10%	C<6,8pF:TK=+100x10 <sup>-6</sup> /°C 6,8pF≤C≤22pF:TK=0x10 <sup>-6</sup> /°C C>22pF:TK=-750x10 <sup>-6</sup> /°C Genomföringstyp/Feed thru
NA 107656	Ferroperm	9/0116,8	63=	± 10%	TK=-150(±60)x10 <sup>-6</sup> /°C
NA 108783	Ferroperm	9/0112,9	400=	±0,25pF	TK=0(±40)x10 <sup>-6</sup> /°C
NA 150880	Ferroperm	9/129,55	250=	± 20%	TK: Olinjär/Non linear
NA 155412	Ferroperm	9/0145,9	12=	-20%+80%	TK: Olinjär/Non linear
NA 155940	Ferroperm	9/0129,8	40=	±20%	TK: Olinjär/Non linear
NA 156140	Ferroperm	9/0129,8	40=	-20%+80%	TK: Olinjär/Non linear
<b>Glimmer Mica</b>					
NB 850471	Soshin	DM 10	100=	5%	C=22-47pF:TK=±100x10 <sup>-6</sup> /°C C=56-82pF:TK=-20/+100x10 <sup>-6</sup> /°C C=100-390pF:TK=0/+70x10 <sup>-6</sup> /°C
NB 850581	Soshin	DM 15	300=	± 5%	C=30-43pF:TK=±100x10 <sup>-6</sup> /°C C=51-82pF:TK=±20/+100x10 <sup>-6</sup> /°C C=100-1800pF:TK=0/+70x10 <sup>-6</sup> /°C
NB 850585	Soshin	DM 15	500=	±5%	C=10-20pF:TK=200x10 <sup>-6</sup> /°C C=30-43pF:TK=100x10 <sup>-6</sup> /°C C=51-82pF:TK=20/+100x10 <sup>-6</sup> /°C C=100-1800pF:TK=0/+70x10 <sup>-6</sup> /°C
<b>Plast Plastic</b>					
NE 105730	Suflex	HS 7/A	30=	± 1%	-150x10 <sup>-6</sup> /°C
NE 765550	Matsuo	MFL 05..k	50=	± 10%	TK: Olinjär/Non linear
NE 765771	Rifa	PFE 216 D	100=	± 1%	TK=-110±30x10 <sup>-6</sup> /°C
NF 775171	ERO	MKT 1822/0 Eingeengt	100=	C<1,0 μF±10% C≥1,0 μF± 5%	Olinjär/Non linear

KONDENSATORER  
CAPACITORS

## C - 500 Automatic

SRA-nr SRA-no	Exempel på fabrikat Example of manufacturer	Typ Type	Arbets- spänning Working voltage ( V )	Kapacitanstolerans Capacitance tolerance	Anmärkning Note
<b>Elektrolyt Electrolytic</b>					
NG 103316	Rifa	PEH 118 GF 410	16=	-10%+100%	Olinjär/Non linear
NG 103335	ERO	EB 220/35-N	35=	-10%+100%	Olinjär/Non linear
NG 103340	Rifa	PEG 118 KD 333	40=	-10%+100%	Olinjär/Non linear
NG 661903	NSF	Typ II	3=	-20%+50%	Tantal
NG 661906	NSF	Typ II	6=	-20%+50%	Tantal
NG 661910	NSF	Typ II	10=	-20%+50%	Tantal
NG 661916	NSF	Typ II	16=	-20%+50%	Tantal
NG 661920	Kemet ERO	K...E 20 ETP	20=	-20%+50%	Tantal
NG 661935	ERO	ETP	35=	-20%+50%	Tantal

## C - 500 Automatic

MOTSTÅND  
RESISTORS

SRA-nr SRA-no	Exempel på fabrikar Example of manufacturer	Typ Type	Effekt vid temp. Power at temp.		Tolerans Tolerance	Max spänning Max voltage (V)	Anmärkning Note
			(W)	(°C)			
Trådlindade fasta Wire-wound fixed							
OB 100644	Vitrohm	253 - 0	1	+125	+2%	130	
OB 420366	Philips	2322 32031...	5,5	+40	4,7-180Ω:±10% 200Ω-15kΩ:±5%	290	
Ytskikt, kol Carbon film							
OD 105455	Beyschlag	SBC 0309	1/8		±5%	250	
OD 500866	Resista	Rn 3	1	+70	±10%	350	
OD 901744	Electrosil	TR 4	1/8	+70	±2%	250	
Massa Composition							
OF 401155	Kamayaohm	RC 1/4 S	0,25	+70	±5%	250	
OF 401166	Kamayaohm	RC 1/4 S	0,25	+70	±10%	250	
OF 401266	Kamayaohm	RC 1/2	0,5	+70	±10%	350	
OF 405055	Vitrohm	GBT	0,5	+70	±5%	350	
Termistor Thermistor							
OJ 130003	Philips	2322 64211...	0,5	+25	±20%		NTC
Vridmotstånd Potentiometers							
OP 500977	Steatit Magnesia	70 WTD-Klog.	0,25	+55	±20%	100	
OP 551066	Bourns	3009	0,75	+25	±20%	500	linjär/linear

C - 500 Automatic

HALVLEDARE  
SEMICONDUCTORS

SRA-nr SRA-no	Exempel på fabrikat Example of manufacturer	Typ Type	Anmärkning Note
<b>Integrerade kretsar</b> Integrated circuits			
TA 160004-2001	RCA	CD 4001 AE	
TA 160004-2011	RCA	CD 4011 AE	
TA 160004-2016	RCA	CD 4016 AE	
TA 160004-2049	RCA	CD 4049 AE	
TA 160004-4016	RCA	CD 4016 AE	
TA 500005-4747	Fairchild RCA	selected $\mu$ A 747	
TA 500006-0748	RCA SGS-Athes	selected $\mu$ A 748	
XTA 865003-1440	Hafo	Hafo 10440	
XTA 865003-1441	Hafo	Hafo 10441	
XTA 865003-1442	Hafo	Hafo 10442	
<b>Dioder</b> Diodes			
VC 602362-0001	Philips	1 N 4148	
VC 602610-0001	Sescosem	BZX 62	
VC 603062-0001	Philips	1 N 4449	
VC 100850-0001	Philips	AAZ 17	
VG 106350-0001	Rifa	PAB 2120	
XVG 106871-0001	Motorola	1N 3492 R	
VL 100604-0002	Motorola	1N 750 A	
VL 100605-0002	Philips	1N 752 A	
VL 100609-0001	Motorola	1N 757 A	

C - 500 Automatic

HALVLEDARE  
SEMICONDUCTORS

SRA-nr SRA-no	Exempel på fabrikat Example of manufacturer	Typ Type	Anmärkning Note
<b>Transistorer Transistors</b>			
YA 405000-0001	Siemens	BC 107 A	
YA 405000-0003	Siemens	BC 107 B	
YA 405000-0004	Siemens	BC 108 B	
YD 400014-0012	Siemens	BC 178 B	
YD 400014-0013	Siemens	BC 177 B	
YD 400015-0001	Motorola	2N 2904	
YD 400015-0051	Motorola	2N 2907 A	
YD 405004-0001	Philips	BF 115	
YD 405007-0001	Philips	BFY 51	
YD 405031-0001	Philips	BFX 89	
YD 405032-0001	Philips	2N 2369	
YD 405034-0031	Philips	2N 2222 A	
YD 405701-0001	SGS	special	
XYE 400007-0001	RCA	2N 5783	
YE 400010-0001	Motorola	special	
YE 405024-0001	Texas	BLY 61 select (R 2237)	
XYE 405039-0001	RCA	2N 5786	

## C - 500 Automatic

ÖVRIGA KOMPONENTER  
OTHER COMPONENTS

SRA-nr SRA-no	Exempel på fabrikat Example of manufacturer	Typ Type	Komponentslag Sort of component
AP 320000-0001	Emilco AB	1/8" C-kula	Stålkula/Steel ball
AY 100003-0001	Odenwälder	23 16 040	Vred/Knob
AY 100003-0010	Odenwälder	50 16 008	Lock/Cap
BC 105004-0001	AMP	141 003-4	Kontakthylsa/Contact socket
BC 205001-0001	Stocko	RBRZ 4772-1-000-0304	Kontaktstift/Contact pin
BC 205001-0004	Stocko	RBRZ 4772-1-000-0307	Kontaktstift/Contact pin
BC 422000-0001	Ansley	741	Kontakthylsa/Contact socket
BF 100000-0002	Ansley	.100 F 401 S 5 A 15	Kabelstycke/Cable piece
BF 100000-0003	Ansley	.100 F 401 S .75 A 17	Kabelstycke/Cable piece
CB 110000-0001	Philips	562 01	Monteringssats/Mounting hardware
CB 119005-0001	Philips	562 45	Underläggsbricka/Distance disc.
CB 210001-0002	Schaffner	WA 322	Kylfläns/Heat dissipator
CB 210003-0001	Thermalloy	4005 T0-5	Kylbricka/Heat sinks
CB 210006-0002	Thermalloy	11 15 B special	Transistorkylare/Heat sink
HA 100008-0001	Amphenol	83GB-74	Hylstag UHF/Receptacle UHF
HH 640000-0001	Mc Murdo	AMP 4957	Kristallhållare/Crystal socket
HM 103017-0001	EBE	FL special	Vridomkopplare/Rotary switch
HM 103017-0003	EBE	FL special	Vridomkopplare/Rotary switch
HM 840500-0071	Schadow	FRRB black/clear	Knapp till tryckomkopplare/Button for push button switch
HM 840500-0074	Schadow	FRRB black/red	Knapp till tryckomkopplare/Button for push button switch
HM 840500-0075	Schadow	FRRB black/blue	Knapp till tryckomkopplare/Button for push button switch
HM 840500-0076	Schadow	FRRB black/orange	Knapp till tryckomkopplare/Button for push button switch
PB 105003-0017	Delevan	1025-28	Induktans/Inductance
PB 105003-0033	Delevan	1025-60	Induktans/Inductance
PJ 7300001-0001	Philips	565 9065/4 B 1	Ferritör/Ferrite tube
PP 400008-11,155	Snelgrove	special	Kristall/Crystal
RC 170002-0003	Rodan	RM3-14V40	Lampa/Lamp T1 14V 40 mA
RC 170002-0004	Oshino	OL-846	Lampa/Lamp T1 3V 8 mA
RC 190002-0002	Alba	A-814-3K	Lampa/Lamp W2x4,6d 12V 35 mA
SB 700007-0001	STC	special	Kristallfilter/Crystal filter